

Список команд управления для интерактивных панелей Lumien

Перечисленные ниже команды применяются для следующих моделей интерактивных панелей Lumien:


- LMP5505FL

Настройки подключения RS232:

- Скорость обмена: 115200 бит/с
- Битов данных: 8 бит
- Паритет: нет
- Стоп бит: 1

Настройки подключения IP:

- IP-адрес: полученный интерактивной панелью
- Порт: 4660



Команда	HEX
SET_POWER_STANDBY	6B303173413030300D
SET_POWER_ON	6B303173413030310D
SET_SOURCE_TO_HDMI	6B303173423030340D
SET_SOURCE_TO_TYPEC	6B303173423030430D
SET_SOURCE_TO_REAR_TYPEC	6B303173423030400D
SET_SOURCE_TO_ANDROID	6B303173423030410D
SET_CONTRAST	6B303173433X3X3X0D
SET_BRIGHTNESS	6B303173443X3X3X0D
SET_SATURATION	6B303173463X3X3X0D
SET_COLOR_MODE_NORMAL	6B303173483030300D
SET_COLOR_MODE_WARM	6B303173483030310D
SET_COLOR_MODE_COLD	6B303173483030320D
SET_COLOR_MODE_USER	6B303173483030330D
SET_COLOR_MODE	6B3031734D3X3X3X0D
SET_BASS	6B3031734A3X3X3X0D
SET_TREBLE	6B3031734B3X3X3X0D
SET_BALANCE	6B3031734C3X3X3X0D
SET_LANGUAGE English	6B3031734E3030300D
SET_LANGUAGE French	6B3031734E3030310D
SET_LANGUAGE Spanish	6B3031734E3030320D
SET_LANGUAGE Traditional Chinese	6B3031734E3030330D
SET_LANGUAGE Simple Chinese	6B3031734E3030340D
SET_LANGUAGE_Portuguese	6B3031734E3030350D
SET_LANGUAGE German	6B3031734E3030360D
SET_LANGUAGE Dutch	6B3031734E3030370D

SET_LANGUAGE Polish	6B3031734E3030380D
SET_LANGUAGE Russia	6B3031734E3030390D
SET_LANGUAGE_Czech	6B3031734E3031300D
SET_LANGUAGE Danish	6B3031734E3031310D
SET_LANGUAGE Swedish	6B3031734E3031320D
SET_LANGUAGE Italian	6B3031734E3031330D
SET_LANGUAGE Romanian	6B3031734E3031340D
SET_LANGUAGE Norwegian	6B3031734E3031350D
SET_LANGUAGE Finnish	6B3031734E3031360D
SET_LANGUAGE Greek	6B3031734E3031370D
SET_LANGUAGE Turkish	6B3031734E3031380D
SET_LANGUAGE Arabic	6B3031734E3031390D
SET_LANGUAGE Japanese	6B3031734E3032300D
SET_LANGUAGE Korean	6B3031734E3032320D
SET_VOLUME	6B303173503X3X3X0D
SET_VOLUME_DOWN	6B303173503230300D
SET_VOLUME_UP	6B303173503230310D
SET_MUTE_OFF	6B303173513030300D
SET_MUTE_ON	6B303173513030310D
SET_NUMBER	6B303173533X3X3X0D
KEY_PAD_UP	6B3031735B3030300D
KEY_PAD_DOWN	6B3031735B3030310D
KEY_PAD_LEFT	6B3031735B3030320D
KEY_PAD_RIGHT	6B3031735B3030330D
KEY_PAD_ENTER	6B3031735B3030340D
KEY_PAD_INPUT	6B3031735B3030350D
KEY_PAD_MENU	6B3031735B3030360D
KEY_PAD_EXIT	6B3031735B3030370D
SET_DATE_YEAR	6B30317358593X3X0D
SET_DATE_MONTH	6B303173584D3X3X0D
SET_DATE_DAY	6B30317358443X3X0D
SET_DATE_HOUR	6B30317359483X3X0D
SET_DATE_MIN	6B303173594D3X3X0D
SET_DATE_SEC	6B30317359533X3X0D
SET_RESET_DEFAULT	6B3031735A3030300D

GET_CONTRAST	6B303167613030300D
GET_BRIGHTNESS	6B303167623030300D
GET_SATURATION	6B303167643030300D
GET_VOLUME	6B303167663030300D
GET_MUTE	6B303167673030300D
GET_CURRENT_INPUT_SOURCE	6B303167683030300D
GET_POWER_STATUS	6B303167693030300D
GET_OPERATION_TIME	6B3031676F3030300D
GET_DATE_YEAR	6B303167704830300D
GET_DATE_MONTH	6B303167704D30300D

GET_DATE_DAY	6B303167704430300D
GET_DATE_HOUR	6B303167714830300D
GET_DATE_MIN	6B303167714D30300D
GET_DATE_SEC	6B303167715330300D
GET_DEVICE_NAME	6B303167723030300D
GET_MAC_ADDR	6B303167733030300D
Возвращаемые значения	
AB07XXXXXXXXX0D	AUTO_WHITE_BALANCE
RETURN_CONTRAST	6B303172613X3X3X0D
RETURN_BRIGHTNESS	6B303172623X3X3X0D
RETURN_SATURATION	6B303172643X3X3X0D
RETURN_VOLUME	0-15
RETURN_MUTE_ON	6B303172673030310D
RETURN_MUTE_OFF	6B303172673030300D
RETURN_INPUT_SOURCE	383031726A3X3X3X0A
RETURN_INPUT_HDMI_NOSIGNAL	383031726A3032340A
RETURN_INPUT_TYPEC_NOSIGNAL	383031726A3031390A
RETURN_INPUT_HDMI_SIGNAL	383031726A3132340A
RETURN_INPUT_TYPEC_SIGNAL	383031726A3131390A
RETURN_INPUT_ANDROID_SIGNAL	383031726A3130410A
RETURN_POWER_ON_STATUS	6B303172693030310D
RETURN_POWER_OFF_STATUS	6B303172693030300D
RETURN_OPERATION_TIME	6B3031726F3X3X3X3X0D
RETURN_DATE_MONTH	6B303172704D3X3X0D
RETURN_DATE_YEAR	6B30317270483X3X0D
RETURN_DATE_DAY	6B30317270443X3X0D
RETURN_DATE_HOUR	6B30317271483X3X0D
RETURN_DATE_MIN	6B303172714D3X3X0D
RETURN_DATE_SEC	6B30317271533X3X0D
RETURN_DEVICE_NAME	6B30317272XXXXXX0D
RETURN_MAC_ADDR	6B30317273XXXXXXXXXXXX0D